







GO - NO GO MATCHBOX

	<p>1. Take a cardboard matchbox drawer and cut two V notches in the middle of its two long edges. Make a clear hole in the centre of both ends of the drawer.</p>	 <p>6. Hold the two ends of the string up-right. If the string is kept loose then the matchbox slides down. But if you tighten the string it rubs against the refill and brakes the matchbox to a stop. This obedient match-box is based on the principle of friction and gravity.</p>
 <p>2. Cut an old ball pen refill equal in size to the width of the drawer.</p>	 <p>3. Fix the refill in the V notches of the drawer with a dab of glue.</p>	
 <p>4. Weave a 70-cm. long string through the two holes of the drawer. The thread should go over the refill. Tie two pieces of folded paper at the two ends for a good grip</p>	 <p>5. Cover the drawer with the outer shell of the matchbox.</p>	